

Build Your Own Quick-Connex® Mini Cordsets

The chart below lists components with which to “build” the exact cordset needed.

How to use:

1. Begin at left with the first column. Write a “**C**” for cordset or a “**R**” for receptacle in the box at the top of the column.
2. From the next column, identify the style. Write the appropriate letter in the box at the top of the column.
3. Select components from all remaining columns, writing the desired letters or numbers chosen in the box at the top of each column.

Example

C	L	2	4	E	05	F	017	
----------	----------	----------	----------	----------	-----------	----------	------------	--

In the sample part number above, **CL24E05F017** is a Mini A size double ended cordset, 4 pole Male straight to Female straight with Super-Trex® Ultra-Gard 16/4 cable #87198, 17 feet length.

Your Selection Goes Here

--	--	--	--	--	--	--	--	--

Type	Style	Ends	No. of Poles	Head Config.	Cable	Unit of Measure	Length	Coupling		
C = Cordset R = Receptacle	L = Mini 2-6 Pole A Size	1 = Single End or Receptacle 2 = Double End	2-12	A = Male Straight AM = Male Straight w/ External Threads B = Male 90° BM = Male 90° w/ External Threads C = Female Straight D = Female 90°	<i>Mini Super-Trex®</i> 01 = 16/2 #87191 02 = 16/3 #87193 05 = 16/4 #87198 07 = 16/5 #87202 09 = 16/6 #87206 11 = 16/7 #87207 12 = 16/8 #87208 13 = 16/9 #88509 14 = 16/10 #88510 15 = 16/12 #88502	M = Meters F = Feet A = Inches	Enter a 3-Digit Code Example: 5 = 005 50 = 050 500 = 500	Blank = Regular S = Stainless Steel P = Plastic		
	M = Mini 6-8 Pole B Size					E = Male Straight to Female Straight EM = Male Straight with External Threads to Female Straight		Other Options: 50 = 18/3 #87192 51 = 18/4 #87197		
	N = Mini 9, 10, 12 Pole C Size					F = Male Straight to Female 90° FM = Male Straight w/ External Threads to Female 90° G = Male 90° to Female Straight GM = Male 90° w/ External Threads to Female Straight H = Male 90° to Female 90° HM = Male 90° w/ External Threads to Female 90°			Receptacle Part Numbers will use PT in place of a Cable Code	
				M = Female Straight to Female Straight N = Female Straight to Female 90° P = Female 90° to Female 90°						