Build Your Own Trex-Onics® Micro M12 Cord Sets

The chart below lists components with which to "build" the exact assembly needed. Begin at left with the first column. Write a **"C"** for cord set or a **"R"** for receptacle in the box at the top of the column. From the next column, identify the style. Write the appropriate letter in the box at the top of the column. Select components from all remaining columns, writing the desired letters or numbers chosen in the box at the top of each column.

1 2 3 4 5 6 7 8 9

TYPE	STYLE	ENDS	POLES	HEAD CONFIG.	CABLE	UOM	LENGTH	COUPLING
C	F	2	5	E	19	F	020	
C = Cord Set	F = DC Micro	1 = Single End (or Receptacle)	Number of Poles: 2 - 8	A = Male Straight B = Male 90° C = Female Straight D = Female 90°	Micro Trex-Onics® 16 = 18/2 (DC) #62022 17 = 18/3 (DC) #62023 18 = 18/4 (DC) #62024 19 = 18/5 (DC) #62025 20 = 18/3 (AC) #62013 21 = 18/4 (AC) #62014 22 = 18/5 (AC) #62015	Unit of Measure:	Enter a three digit code in the box above.	Blank = Regular
R = Receptacle	G = AC Micro	2 = Double End				M = Meters		S = Stainless Steel
				E = Male Straight to Female Straight F = Male Straight to Female 90° G = Male 90° to Female Straight H = Male 90° to Female 90°		F = Feet		
						A = Inches	5 = "005"	P = Plastic
							50 = "050"	
							500 = "500"	
				 M = Female Straight to Female Straight N = Female Straight to Female 90° P = Female 90° to Female 90° 				
					Other Trex-Onics® Cable Options 60 = 22/8 (DC) Unshielded #60018			
				Micro Receptacles — Micros Only Q = Female Back Mount R = Male Panel Mount S = Male Switch Mount T = Female Panel Mount	#60018 61 = 22/8 (DC) 62 = 22/3 (DC) Shielded #60019 #62033 63 = 18/3 (DC) 70 = 22/4 (DC) Shielded #62003 #62034 72 = 18/4 (DC) 71 = 22/5 (DC) Shielded #62004 #62035 73 = 18/5 (DC) Shielded #62005			

In the sample part number above, **CF25E19F020** is a DC micro, double ended cord set, 5 poles, male straight to female straight with 18/5 Trex-Onics cable (#62025), 20 feet long.