

## M12 DC Micro Cordsets

# Build Your Own Quick-Connex® M12 DC Micro High Temperature Chem-Gard® Cordsets

The chart below lists components with which to “build” the exact cordset needed.

### How to use:

1. Begin at left with the first column. Write a “**C**” for cordset or a “**R**” for receptacle in the box at the top of the column.
2. From the next column, identify the style. Write the appropriate letter in the box at the top of the column.
3. Select components from all remaining columns, writing the desired letters or numbers chosen in the box at the top of each column.

### Example

<b>C</b>	<b>F</b>	<b>2</b>	<b>4</b>	<b>E</b>	<b>75</b>	<b>M</b>	<b>002</b>	
----------	----------	----------	----------	----------	-----------	----------	------------	--

In the sample part number above, **CF24E75M002** is a M12 DC Micro cordset, double end 4 pole Male straight to Female straight with Chem-Gard® 18/4 cable #42804DC, 2 meters length.

### Your Selection Goes Here

--	--	--	--	--	--	--	--	--

Type	Style	Ends	No. of Poles	Head Config.	Cable	Unit of Measure	Length	Coupling
<b>C</b> = Cordset <b>R</b> = Receptacle	<b>F</b> = DC Micro	<b>1</b> = Single End or Receptacle <b>2</b> = Double End	<b>4</b>	<b>A</b> = Male Straight <b>B</b> = Male 90° <b>C</b> = Female Straight <b>D</b> = Female 90° <b>E</b> = Male Straight to Female Straight <b>F</b> = Male Straight to Female 90° <b>G</b> = Male 90° to Female Straight <b>H</b> = Male 90° to Female 90°	<b>75</b> = Chem-Gard® 18/4 #42804DC  Receptacles will use Cable Code 75 to note single conductor Chem-Gard® 18AWG cable as Pigtails	<b>M</b> = Meters <b>F</b> = Feet <b>A</b> = Inches	Enter a 3-Digit Code  Example: 5 = <b>005</b> 50 = <b>050</b> 500 = <b>500</b>	Blank = Regular  <b>S</b> = Stainless Steel